



# Standard electromagnetic ballast for compact fluorescent applications

## BPL EM ballasts for CFL, PL-T, PL-S and PL-C lamps

This standard, reliable, long-life electromagnetic ballast for compact fluorescent lamps provides excellent performance with 2-pin and 4-pin CFLni lamps.

### Benefits

- Reliable electrical and mechanical performance
- Optimum lamp performance under optimum temperature conditions
- Fits compact luminaires

### Features

- Long lifetime
- Compact design
- Quick and easy wiring
- High-quality screw-in or insert contact

### Application

- Retail
- Offices
- Industry
- Home

# BPL EM ballasts for CFL, PL-T, PL-S and PL-C lamps

## Versions



BPL 26W 220V B2 SC

## Dimensional drawing

A1

Product	D1	C1	A1	A2	A3	A4	B1
BPL 13W 220V B2 SC	4.3 mm	28.0 mm	85.0 mm	75.0 mm	31.0 mm	32.0 mm	39.0 mm
BPL 18W 220V B2 SC	4.3 mm	28.0 mm	85.0 mm	75.0 mm	31.0 mm	32.0 mm	39.0 mm

### Approval and Application

Energy Efficiency Index B2

### Operating and Electrical

Input Frequency 50 Hz

Input Voltage 220 V

### Mechanical and Housing

Housing L 85x39x28

## System characteristics

Order Code	Full Product Name	Rated Ballast-Lamp Power
913710121550	BPL 13W 220V B2 SC	13 W

Order Code	Full Product Name	Rated Ballast-Lamp Power
913710121650	BPL 18W 220V B2 SC	18 W

## BPL EM ballasts for CFL, PL-T, PL-S and PL-C lamps

